

5 This patent application is related to U.S. Patent Application No.
_____, filed _____ (Attorney Docket No. PU000143)
which is incorporated herein by reference in its entirety.

10 1. Field of the Invention

2. Description of the Prior Art

15 In a system for recording a received video signal, such as a video cassette recorder (VCR), a video input device within a computer system and the like, it is sometimes desirable to avoid recording at least portions of the received video signal. For example, U.S. Patent No. 4,283,735 discloses a technique for detecting color information within a received video signal including both color and black and white
20 imagery such that a video tape recorder may selectively record only non-color video imagery. In this manner, the video tape recorder records only a desired monochrome portion of a movie or broadcast by avoiding the recording of station breaks or commercials interspersed therein, which station breaks and commercials are typically provided in color.

25 Unfortunately, the above-referenced "commercial killer" technique is useful only in those situations where desirable and undesirable portions of a video program may be determined with respect to the presence or absence of color (or monochrome) imagery in a video signal.

SUMMARY OF THE INVENTION

The invention comprises a system and method for eliminating poor or non-existent video, or selected video sections, from a video recording, such as a second generation video recording. The present invention operates to determine whether synchronizing pulses, such as vertical and/or horizontal synchronizing pulses indicative of the presence of a television signal are received. Moreover, in a case of received synchronizing pulses, those pulses are evaluated to determine if synchronizing pulse distortions indicative of likely video signal distortions are present. In a case of absent synchronizing pulses or distorted synchronizing pulses, a recording device is paused, such that a recording medium does not include blank portions or poor quality portions. The absence of synchronizing pulses indicates that the recording device is not receiving a valid video signal. Distorted synchronizing pulses indicate that, for example, a received video signal comprises a trick mode (e.g., fast forward, fast play or rewind), which trick mode signal does not convey useful information and should not be recorded. Additionally, other distortions indicative of transmission problems or other video signal degradations further indicate that such video signal should not be recorded.

Apparatus according to one embodiment of the invention comprises: an input circuit for receiving a video signal indicative of playback of a first recorded medium; a detection circuit for detecting a horizontal synchronization signal component of said video signal; and a control circuit for controlling pauses in recording of video information from the video signal responsive to detecting the horizontal synchronizing signal.

BRIEF DESCRIPTION OF THE DRAWINGS

The teachings of the present invention can be readily understood by considering the following detailed description in conjunction with the accompanying drawings, in which:

FIG. 1 depicts a block diagram of a video recording system according to an embodiment of the invention;

FIG. 2 depicts a high level block diagram of a controller suitable for implementing the functionality of the detector 100 of FIG. 1; and

FIG. 3 depicts a high level block diagram of a SYNC evaluation module suitable for use in the system of FIG. 1.

5 To facilitate understanding, identical reference numerals have been used, where possible, to designate identical elements that are common to the figures.

DETAILED DESCRIPTION

The invention will be described within the context of a television receiver
10 operating according to the National Television Standards Committee (NTSC) standards. It will be appreciated by those skilled in the art that the invention is applicable to other television standards, such as the Phase Attenuating Line (PAL) and Sequential Color With Memory (SECAM) standards. Moreover, it will be appreciated by those skilled in the art that the invention is applicable to any video signal including
15 periodically occurring synchronizing (SYNC) components wherein perturbations in the periodicity or shape of the synchronizing components may reasonably be construed as reflecting the presence or quality of associated video signal.

FIG. 1 depicts a high level block diagram of a video recording system according to an embodiment of the invention. Specifically, FIG. 1 depicts a high level block
20 diagram of a video recording system 100 comprising a first video device 110 that sources a video signal and, optionally, audio, control and other associated signals to a second video device via an audio/video (A/V) cable 115. The second video device comprises a tuner/input device 120, an audio processor 125, a video processor 130, a synchronizing component (SYNC) detection and evaluation module 135, a controller
25 140 and a recording device 145.

The first video device 110 may comprise any video source, such as a video cassette recorder (VCR), camcorder, digital video disk (DVD) player, computer video output device and the like. It is assumed that the first video device 110 provides at least an output video signal including image portions and synchronizing portions, such
30 as an analog NTSC video signal or digital video stream. The output video signal may

0975439 113900

signal video to produce a processed video signal V which is coupled to the recording device 145.

The recording device 145 cooperates with a medium 150, such as a video cassette, hard disk drive, floppy disk drive, flash memory device, compact disk, video disk or any other recording medium. The recording device 145 operates to record, onto the medium 150, information representative of the processed video signal V and, if present, the processed audio signal A.

The recording device 145, in response to a control signal C produced by the controller 140, enters one of a record mode and a record-pause (or pause) mode. Thus, the controller 140 is used to selectively pause the recording device 145 such that received video V and audio A is selectively stored on the medium 150.

The SYNC evaluation module 135 and controller 140 operate to effect a synchronization component detection and evaluation function, as well as a control function.

15 The controller 140 may selectively cause the recording device 145 to begin recording at a given time. In this manner, portions of the audio and video information provided by the first video device 110 may be recorded onto the medium 150, while other portions are not recorded. For example, it is desirable to pause the recording process when the received video signal is distorted, when the received video signal
20 comprises a trick play signal such as fast forward, rewind, fast play and the like, when the received video signal includes undesirable content such as commercials or station breaks, or, generally, when the received video signal is anything other than a normal (i.e., play mode) video signal.

The SYNC evaluation module 135 receives the video signal VIDEO provided by
25 the timer/input device 120. The SYNC evaluation module 135 processes at least the
synchronizing components associated with the received video signal VIDEO to
evaluate the presence and/or quality of the synchronizing component. For example, in
the case where the SYNC evaluation module determines that horizontal and/or
vertical synchronizing information does not exist within the video signal VIDEO, then it

In the case of the SYNC evaluation module 135 determining that synchronizing information does not exist or is unacceptable due to distortion or other reasons, a SYNC quality output signal SQ indicates that such condition exists. In the case where the SYNC evaluation module 135 determines that synchronizing information within the video signal is present and is of sufficient quality (e.g., within threshold limits for SYNC "stretch," SYNC pulse shape and other factors), the SYNC quality signal SQ indicates this condition.

20
25
30

The SYNC evaluation module 135 may also be implemented according to the SYNC detector described in commonly assigned U.S. Patent Application No. _____, filed _____, which is incorporated herein by reference in its entirety. Briefly, the disclosed detector operates to detect changes in the temporal spacing of synchronizing pulses, such as vertical and/or horizontal synchronizing pulses within a television or video signal. Such changes may comprise, for example, a gross change in the time period associated with the synchronizing signals (i.e., large changes within the time intervals separating successive synchronizing signals). Such changes may also comprise, for example, changes in the pulse width of synchronizing pulses, such as horizontal synchronizing pulses and/or vertical synchronizing pulses. For example, in the case of video tape stretch or other physical

The controller 140 of FIG. 1 is responsive to the SYNC quality signal SQ provided by the SYNC evaluation module 135. In response to a SYNC quality signal SQ indicative of valid and acceptable synchronization information within the video signal VIDEO, the controller 140 causes the recording device 145 to enter or maintain a record mode of operation. In response to a SYNC quality signal SQ indicative of absent or unacceptable synchronization information within the video signal, the controller 140 causes the recording device 145 to enter a record-pause or pause mode of operation.

It is noted that in the case of the first video device 110 and second video device being responsive to similar remote control signals (e.g., both video devices being manufactured by the same company or adhering to the same control standards), the control signals C₁ and C₂ may simultaneously cause both the first video device 110 and second video device to record. In this instance, two recordings of video information provided to the first video device via an external source are made.

In one application of the invention, where the first video device 110 comprises a camcorder including a plurality of scenes or recorded segments including "white space," or other video glitches, the second video device will operate to record only the valid video information conveyed by the first video device. That is, where the video
 5 information associated with the first video device includes invalid portions of video, the second video device will not record those invalid portions of video data. In this manner, the invention is operable to "clean up" sequences of video imagery including invalid portions.

FIG. 2 depicts a high level block diagram of a controller suitable for
 10 implementing the functionality of the SYNC evaluation module 135 and controller 140 of the system 100 of FIG. 1. The controller 200 of FIG. 2 implements the synchronization component evaluation method described below with respect to FIG. 3. Alternatively, the controller 200 of FIG. 2 implements methods discussed in U.S. Patent Application No. _____, filed
 15 _____, which is incorporated herein by reference in its entirety. The controller 200 also implements control functionality useful in adapting the operation of the recording device 145 to the presence and/or quality of an evaluated synchronizing component of a video signal, or to a control signal provided by, for example, a remote control device.

20 The controller 200 of FIG. 2 comprises a processor 220 as well as memory 230 for storing various detection and control programs 235. The processor 220 cooperates with conventional support circuitry 240 such as power supplies, clock circuits, cache memory and the like as well as circuits that assist in executing the software routines stored in the memory 230. As such, it is contemplated that some of
 25 the process steps discussed herein as software processes may be implemented within hardware, for example, as circuitry that cooperates with the processor 220 to perform various steps. The controller 200 also contains input/output (I/O) circuitry 210 that forms an interface between the various functional elements required to implement the detector function described above with respect to FIG. 1. For example, the controller

00627" 63439 112000

200 of FIG. 2 may be used to replace elements 135 and 140 of the system 100 of FIG. 1.

Thus, the controller 200 of FIG. 2 receives a video signal VIDEO having associated with it synchronizing components. The synchronizing components may
5 comprise horizontal and vertical synchronizing. The controller 200 processes the video signal VIDEO to produce a control signal C indicative of an appropriate operating mode of the recording device 145

Although the controller 200 of FIG. 2 is depicted as a general purpose computer that is programmed to perform various detection and processing functions
10 in accordance with the present invention, the invention can be implemented in hardware as, for example, an application specific integrated circuit (ASIC). As such, the process steps described herein are intended to be broadly interpreted as being equivalently performed by software, hardware, or a combination thereof.

FIG. 3 depicts a high level block diagram of a SYNC evaluation module suitable
15 for use in the system of FIG. 1. Specifically, the SYNC evaluation module 135 of FIG. 3 receives the video signal VIDEO, evaluates the synchronization information within the video signal VIDEO, and provides an output signal SQ indicative of the quality of the evaluated synchronization information.

The SYNC evaluation module 135 of FIG. 3 comprises a horizontal-vertical (H-V)
20 SYNC separator 310, a count down timer 315, a vertical lock detector 320, a horizontal lock detector 325, an oscillator or clock circuit 330, a horizontal error counter 335, a vertical error counter 340 and a logical AND gate 345. Optionally, the SYNC evaluation module 135 includes an optional horizontal and/or vertical reference generator 380. It will be appreciated by those skilled in the art that various common
25 support circuitry, such as debouncing or similar circuitry is not shown for clarity.

The H-V SYNC separator 310 separates the horizontal H and vertical V synchronization pulses included within the received video signal VIDEO. A signal comprising at least the separated horizontal synchronization pulses H is coupled to the horizontal lock detector 325 and the countdown timer 315. A signal comprising at
30 least the separated vertical synchronization pulses V is coupled to the vertical lock

00621 58453 60

detector 320. The clock circuit 330 provides a clock signal to the horizontal lock detector 325.

The horizontal lock detector 325 utilizes the provided clock signal CL to determine time intervals within which a horizontal synchronizing pulse is expected to arrive. The H-lock detector 325 notes the synchronizing occurrence of a horizontal pulse via edge or level triggering circuitry (not shown). The H-lock detector 325 provides an output signal H_{ERROR} indicative of whether an expected horizontal SYNC pulse H failed to arrive.

The countdown timer 315 produces an output signal COUNT each time a predetermined number of horizontal SYNC pulses H are received. For example, it is known that in the NTSC system there are 262.5 horizontal scan lines per vertical SYNC pulse. This does not include the "serration pulses" which are provided at two times the horizontal scan rate. If the serration pulses are included as pulses to be counted between vertical pulses, then there are about eight additional midway pulses per vertical scan to even out the scan differences between horizontal scan and vertical scan for a complete picture. These extra pulses compensate for the "half line" difference indicated by the 252.5 horizontal scan line per vertical SYNC pulse metric. It is noted that it takes two vertical scans to fill out the picture (i.e., interlaced image). The NTSC system provides 525 lines for a complete picture and vertical retrace blanking. Thus, the ratio of 525 horizontal scan lines per two vertical SYNC pulses is used by the countdown timer 315 to provide an indication to the vertical lock detector 320 of the time that a vertical SYNC pulse is expected to be received. This ratio may be readily adapted to other video transmission/display systems, as will be appreciated by those skilled in the art.

25 The vertical lock detector 320 utilizes the provided countdown timer output
signal Count to determine time intervals within which a vertical synchronizing pulse is
expected to arrive. The V-lock detector 320 notes the arrival or occurrence of a
vertical synchronizing pulse via edge or level triggering circuitry (not shown). The V-lock
detector 320 provides an output signal V_{ERROR} indicative of whether an expected
30 vertical SYNC pulse failed to arrive.

The vertical error counter 340 counts the number of vertical errors within a given time period and compares that number to a vertical error threshold level V_{th} . If a number of errors indicated by the V-lock detector error signal V_{error} exceeds the vertical error threshold level V_{th} within the given time interval, a vertical error signal V_e indicates such error conditions.

The logical AND gate 345 (or any logical equivalent) provides an output signal having two states, a "good SYNC" state and a "bad SYNC" state. In the event of a bad horizontal synchronizing signal (as indicated by error counter 335) or a bad vertical synchronizing signal V (as indicated by error counter 340), the output signal SQ of the logic gate 345 indicates the "bad SYNC" state.

The controller 140 of FIG. 1 is responsive to the SYNC quality signal SQ provided by the SYNC evaluation module 135. In response to a SYNC quality signal SQ indicative of valid and acceptable synchronization information within the video signal VIDEO, the controller 140 causes the recording device 145 to enter or maintain a

It is noted that in the case of the first video device 110 and second video device being responsive to similar remote control signals (e.g., both video devices being manufactured by the same company or adhering to the same control standards), the control signals C₁ and C₂ may simultaneously cause both the first video device 110 and second video device to record. In this instance, two recordings of video information provided to the first video device via an external source are made.

In one embodiment of the invention, the SYNC evaluation module 135 comprises a timer, for associating temporal information with each of a sequence of received synchronization pulses; a first differencer, for measuring temporal differences between successive synchronization pulses to determine respective synchronization pulse timing intervals; a second differencer, for measuring temporal differences between successive synchronization pulse timing intervals; and a comparator, for producing a control signal indicative of whether differences between successive synchronization pulse timing intervals exceed a threshold level. It is noted that the first and second differencers may be comprised of respective pairs of memory elements coupled to a subtractor. The first differencer memory elements store temporal information associated with successive synchronization pulses, while the second differencer memory elements store temporal information associated with successive synchronization pulse timing intervals. It is also noted that the pulse width of vertical and/or horizontal synchronizing pulses may be measured such that comparisons between successive respective vertical and/or horizontal synchronizing pulses may determine that, due to changes in measured pulse widths, received video

In one application of the invention, where the first video device 110 comprises a camcorder including a plurality of scenes or recorded segments including "white
5 space," or other video glitches, the second video device will operate to record only the valid video information conveyed by the first video device. That is, where the video information associated with the first video device includes invalid portions of video, the second video device will not record those invalid portions of video data. In this manner, the invention is operable to "clean up" sequences of video imagery including
10 invalid portions.

Although various embodiments which incorporate the teachings of the present invention have been shown and described in detail herein, those skilled in the art can readily devise many other varied embodiments that still incorporate these teachings.